

IZI-Touch



IZI-Control over:

- 64 Scenes and 12 Sequences over 6 individual Playbacks
- 32 Virtual Contactinputs (to Toggle, Pulse and Trigger Scenes, Sequences, Softpatches, Macro's, Scheduler, Timers and Contact outputs)
- 1024 channels over sACN / Art-Net (512 channels over DMX)

The IZI-way to control your lights

IZI-Touch – Intuitive, Customizable Control at Your Fingertips

The IZI-Touch is a sleek touchscreen device that connects to an IZI-AccessPro over the network. Using the IZI-Supervisor, you can design your own custom interface with buttons, faders, images, and labels—tailored exactly to your installation. Functions can even be protected with a PIN code for secure operation.

One of its greatest strengths appears when multiple IZI-Touch units are linked to the same IZI-AccessPro: every button and fader stays perfectly synchronized across all devices. The screen layout and configuration are automatically downloaded from the IZI-AccessPro, keeping everything consistent and easy to manage.

Whether in theaters, hotels, cinemas, or large multi-zone venues, the IZI-Touch offers effortless, elegant lighting control wherever you need it. The **IZI-Touch** is a freely programmable touchscreen control panel for wall mounting, suitable for use in combination with the **IZI-AccessPro** light controller/gateway.

Features:

- **5" Wall Mounted IZI-Touch Control Panel**
Landscape or portrait mounted on standard EU installation boxes
- **High resolution wide angle IPS touch display**
With 1280 x 720 pixels, 10-point capacitive touchscreen, high contrast and 500nits brightness
- **PoE Ethernet connection**
No external power supply needed
- **Automatic synchronization between multiple IZI-Touch displays**
Up to 4 IZI-Touch display may connected to an IZI-AccessPro controller
- **Take full control over most features of the IZI-AccessPro**
64 scenes, 12 sequences, 6 individual playbacks, 32 virtual contactinputs to toggle, pulse and trigger scenes, sequences, softpatches, macro's, scheduler, timers and contact outputs
- **Freely programmable display layout:**
 - In total maximum 32 objects with Buttons, Border buttons, Faders, Master faders and labels
 - Programmable button actions with Toggle, Pulse, Trigger and up to 3 sets of Radiobutton groups all in Normally open (NO) and closed (NC) actions
 - Programmable colours for buttons, faders, labels and fonts, all for active and inactive states and groups, borders and background.
 - Screen grid size of 12 x 12 with up to 16 groups, each with a grid size of 12 x 12
 - Timeout and sleepmode settings with optional PIN-code levels and uploadable custom screensaver image